

## Comparison matrix for amendment to the safety regulations on nuclear reactor facilities for Fukushima Daini Nuclear power Station(1/3)

Before amendment	After amendment	Note
(N.A.)	<p>(Improvement of system under Station Blackout)</p> <p>Article 17-2</p> <p>The organization shall draw up plan for each of the following in order to improve system for maintaining reactor facilities under circumstances where tsunami cause loss of function to all the facilities receiving AC power, all the reactor cooling facilities utilizing seawater and all the facilities for the cooling spent fuel pool ( "Station Blackout " ).</p> <p>(1) Allocate staff in order to maintain reactor facilities under Station Blackout.</p> <p>(2) Train staff who operate to maintain reactor facilities under Station Blackout.</p> <p>(3) Install power source cars, fire-fighting vehicles, fire fighting hoses and other equipments necessary for operation to maintain reactor facilities under Station Blackout.</p> <p>2. The organization shall conduct activities to maintain reactor facilities under Station Blackout based on the plans mentioned above.</p> <p>3. The organization shall conduct periodic evaluation on the matters mentioned in Paragraph 1. and 2. and based on such evaluation, take necessary measures.</p>	<p>Amendment in connection with the amendment to Rules on the Installation and Operation of Commercial Power Reactors (amended on March 30<sup>th</sup>, 2011)</p>

Comparison matrix for amendment to the safety regulations on nuclear reactor facilities for Fukushima Daini Nuclear power Station(2/3)

Before amendment	After amendment	Note																																
<p>(Emergency Diesel Generator part 2) Article 61:</p> <ol style="list-style-type: none"> <li>When the status of the nuclear reactor is cold shutdown or during fuel replacement, the Emergency Diesel Generator shall satisfy Operating Restrictions set forth in chart 61-1.</li> <li>In order to confirm that the Emergency Diesel Generator satisfies the Operating Restrictions set forth in the foregoing, the following shall be executed: (1) The chief shift operator shall confirm that the Emergency Diesel Generator connected to the emergency AC high voltage bus required in accordance with Article 66 satisfies matters set forth in chart 61-2.</li> <li>In the event that the chief shift operator decides that the Emergency Diesel Generator does not satisfy the Operating Restrictions set forth in item 1 above, the chief shift operator shall execute measures set forth in chart 61-3.</li> </ol> <p>Chart 61-1</p> <table border="1"> <thead> <tr> <th>Item</th> <th>Operating Restriction</th> </tr> </thead> <tbody> <tr> <td>AC power</td> <td>The Emergency Diesel Generator connected to the emergency AC high voltage bus required in accordance with Article 66 is capable of operation</td> </tr> </tbody> </table> <p>(abbreviated)</p> <p>Chart 61-3</p> <table border="1"> <thead> <tr> <th>Conditions</th> <th>Required action</th> <th>Timeframe</th> </tr> </thead> <tbody> <tr> <td rowspan="4">A. In the event that <u>the Emergency Diesel Generator cannot be operated</u></td> <td>A1. To commence the restoration work of the Emergency Diesel Generator back to the operable condition</td> <td>ASAP</td> </tr> <tr> <td>and A2. To cancel pattern coordination</td> <td>ASAP</td> </tr> <tr> <td>and A3. To cancel irradiated fuel related works in the reactor building</td> <td>ASAP</td> </tr> <tr> <td>and A4. To prohibit opening isolation valves on piping comprising the reactor coolant pressure boundary connected to the reactor pressure vessel below the top of active fuel</td> <td>ASAP</td> </tr> </tbody> </table>	Item	Operating Restriction	AC power	The Emergency Diesel Generator connected to the emergency AC high voltage bus required in accordance with Article 66 is capable of operation	Conditions	Required action	Timeframe	A. In the event that <u>the Emergency Diesel Generator cannot be operated</u>	A1. To commence the restoration work of the Emergency Diesel Generator back to the operable condition	ASAP	and A2. To cancel pattern coordination	ASAP	and A3. To cancel irradiated fuel related works in the reactor building	ASAP	and A4. To prohibit opening isolation valves on piping comprising the reactor coolant pressure boundary connected to the reactor pressure vessel below the top of active fuel	ASAP	<p>(Emergency Diesel Generator part 2) Article 61:</p> <ol style="list-style-type: none"> <li>When the status of the nuclear reactor is cold shutdown or during fuel replacement, the Emergency Diesel Generator shall satisfy Operating Restrictions set forth in chart 61-1.</li> <li>In order to confirm that the Emergency Diesel Generator satisfies the Operating Restrictions set forth in the foregoing, the following shall be executed: (1) The chief shift operator shall confirm that the Emergency Diesel Generator connected to the emergency AC high voltage bus required in accordance with Article 66 satisfies matters set forth in chart 61-2.</li> <li>In the event that the chief shift operator decides that the Emergency Diesel Generator does not satisfy the Operating Restrictions set forth in item 1 above, the chief shift operator shall execute measures set forth in chart 61-3. *1: Emergency Diesel Generator means the emergency diesel generator for system A, B and HPCS.</li> </ol> <p>Chart 61-1</p> <table border="1"> <thead> <tr> <th>Item</th> <th>Operating Restriction</th> </tr> </thead> <tbody> <tr> <td>AC power</td> <td><u>Two emergency generation facilities including the Emergency Diesel Generator connected to the emergency AC high voltage bus required in accordance with Article 66 are capable of operation</u></td> </tr> </tbody> </table> <p><u>*2: emergency generation facilities means the Emergency Diesel Generator and emergency generators that has sufficient capacity to supply electricity. The emergency generators may be shared between several Units.</u></p> <p>(abbreviated)</p> <p>Chart 61-3</p> <table border="1"> <thead> <tr> <th>Conditions</th> <th>Required action</th> <th>Timeframe</th> </tr> </thead> <tbody> <tr> <td rowspan="4">A. In the event that <u>the Operating Restrictions are not satisfied</u></td> <td>A. To commence measures <u>to satisfy the Operating Requirements</u></td> <td>ASAP</td> </tr> <tr> <td>and A2. To cancel pattern coordination</td> <td>ASAP</td> </tr> <tr> <td>and A3. To cancel irradiated fuel related works in the reactor building</td> <td>ASAP</td> </tr> <tr> <td>and A4. To prohibit opening isolation valves on piping comprising the reactor coolant pressure boundary connected to the reactor pressure vessel below the top of active fuel</td> <td>ASAP</td> </tr> </tbody> </table>	Item	Operating Restriction	AC power	<u>Two emergency generation facilities including the Emergency Diesel Generator connected to the emergency AC high voltage bus required in accordance with Article 66 are capable of operation</u>	Conditions	Required action	Timeframe	A. In the event that <u>the Operating Restrictions are not satisfied</u>	A. To commence measures <u>to satisfy the Operating Requirements</u>	ASAP	and A2. To cancel pattern coordination	ASAP	and A3. To cancel irradiated fuel related works in the reactor building	ASAP	and A4. To prohibit opening isolation valves on piping comprising the reactor coolant pressure boundary connected to the reactor pressure vessel below the top of active fuel	ASAP	<p>To reflect the order from NISA “Regarding interpretation of safety regulations on emergency generating facilities” April 9<sup>th</sup>, 2011</p>
Item	Operating Restriction																																	
AC power	The Emergency Diesel Generator connected to the emergency AC high voltage bus required in accordance with Article 66 is capable of operation																																	
Conditions	Required action	Timeframe																																
A. In the event that <u>the Emergency Diesel Generator cannot be operated</u>	A1. To commence the restoration work of the Emergency Diesel Generator back to the operable condition	ASAP																																
	and A2. To cancel pattern coordination	ASAP																																
	and A3. To cancel irradiated fuel related works in the reactor building	ASAP																																
	and A4. To prohibit opening isolation valves on piping comprising the reactor coolant pressure boundary connected to the reactor pressure vessel below the top of active fuel	ASAP																																
Item	Operating Restriction																																	
AC power	<u>Two emergency generation facilities including the Emergency Diesel Generator connected to the emergency AC high voltage bus required in accordance with Article 66 are capable of operation</u>																																	
Conditions	Required action	Timeframe																																
A. In the event that <u>the Operating Restrictions are not satisfied</u>	A. To commence measures <u>to satisfy the Operating Requirements</u>	ASAP																																
	and A2. To cancel pattern coordination	ASAP																																
	and A3. To cancel irradiated fuel related works in the reactor building	ASAP																																
	and A4. To prohibit opening isolation valves on piping comprising the reactor coolant pressure boundary connected to the reactor pressure vessel below the top of active fuel	ASAP																																

Comparison matrix for amendment to the safety regulations on nuclear reactor facilities for Fukushima Daini Nuclear power Station(3/3)

Before amendment	After amendment	Note
<p style="text-align: center;">Supplementary Provision</p> <p><u>Supplementary Provision (June 14<sup>th</sup>, 2010 Ver. 2 to the original dated May 26<sup>th</sup>, 2010)</u> (Implementation date) Article 1 This regulation shall be effective <u>as from July 1<sup>st</sup>, 2010.</u></p> <p><u>Supplementary Provision (January 22<sup>nd</sup>, 2010 Ver. 8 to the original dated December 16<sup>th</sup>, 2009)</u> (Implementation date) Article 1 <u>4. As to matters set forth in chart 39-2 in Article 39 regarding Unit 4, that will be applicable from the major maintenance of Unit 4 as per item 1, Article 54 of the Electricity Business Act. Before that, the predicate rules be observed.</u></p>	<p style="text-align: center;">Supplementary Provision</p> <p><u>Supplementary Provision (Month, Date, Year Ver. [ ] to the original dated Month, Date, Year)</u> (Implementation date) Article 1 1. This regulation shall be effective <u>as from the next date of approval by the Minister of METI.</u> 2. <u>Until the commencement of operation of the emergency generator in accordance with Article 61, other Unit s Emergency Diesel Generator or a movable generator may be deemed as the emergency generator.</u></p>	<p>The effective date is set out in item 1, Article 1 of the Supplementary Provision. Item 2, Article 1 of the Supplementary Provision sets out the transient arrangement</p> <p>Deleted because chart 39-2 in Article 39 is already applicable to Unit 4</p>